

# Hard Drive Destroyer

Secure Physical Destruction Tool for HDDs

## Features:

- Complete Physical Destruction
- Secure Data Deletion
- Quick and Safe Operation



Finishes a “V” shape damage in less than 10 seconds by one button push. No chance of data recovery.

### Easy & Fast

- One push button easy operation
- Less than 10 seconds destruction cycle

### Secure Destruction

- Industrial grade “V” shape bending harmer
- Complies with HK and international standards

### Process Monitoring

- Power Lock for access control
- LED status indication light
- Overheat warning and emergency stop

This destroyer model, DED-HD2, physically destroys a hard drive by bending, breaking and mangling both its external and internal parts. The data platters are bent and separated from the hub, the HDD housing is cracked, the PC board is broken and the read/write heads are mangled.



## Standard Compliance

ISO  
DoD 5220.22M  
DoD Emergency Destruction Guidelines  
NSA/CSS SDDM 9-12  
NIST SP 800-36 / 800-88

## More Features

Embedded usage counter  
Built-in spot light  
Less than 40dB low noise  
Less than 27kg super light weight  
Compact design for office environment

## Specifications

Item	Specifications
<b>Model</b>	DED-HD2
<b>Destruction Method</b>	Automated Gear Power transfer
<b>Target Media</b>	Notebook HDD (2.5 inch) Desktop HDD (3.5 inch) Storage HDD (3.5 x 1 inch) Storage HDD (3.5 x 1.6 inch), SSD, etc. Thickness of hard drive up to 35mm (2 thinner HDDs at same time)
<b>Time for Destruction</b>	Approx. 10 sec/job (Cycle time: 20 sec)
<b>Operation Environment</b>	Temperature: 5 to 40°C, Humidity: 10 to 80% (Non Condensing)
<b>Cooling System</b>	Cooling Fan system design
<b>Consumable</b>	45 degree V-Shape Destruction Hammer
<b>Power Requirement</b>	AC 110V/220V; 50/60 Hz
<b>Weight</b>	26.7kg
<b>Dimension</b>	228(W) x 347(D) x 289(H) mm
<b>Accessories</b>	User's Manual / Warranty Card
<b>MAX # of Continuous Operations</b>	200 units
<b>MAX # of Operation per day</b>	500 units
<i>Specifications are subject to change without notice.</i>	